

单面尺寸: 140*100mm
 工艺: 风琴页
 书写纸

WINGMAN 15

Bedienungsanleitung

15,6" Zoll tragbarer Monitor

Herzlichen Glückwunsch zu Ihrem neuen Wingman! Für den bestmöglichen Start lesen Sie bitte diese Bedienungsanleitung vor Inbetriebnahme des Gerätes aufmerksam durch.

Inhalt

15,6" Zoll tragbarer Monitor

15,6" Zoll

USB-C auf USB-C Kabel
VIDEO & AUDIO & STROM

USB-C auf USB-A Kabel
NUR Strom

Mini HDMI auf HDMI cable
VIDEO & AUDIO

Bedienungsanleitung

Lederhülle & -ständer
1

Netzteil
(optional)

Monitor Bedienung

15,6" Zoll

① USB-C port (nur Strom)

② Menü-Rad

③ Zurück/ Power Knopf

④ Mini HDMI Anschluss

⑤ USB-C Anschluss (volle USB-C Funktion)

⑥ 3.5mm Kopfhöreranschluss

- USB-C port (nur für Daten):** provide external power supply support; support reverse charging; compatible with PD2.0 power supply protocol; support 5-20V voltage input;
- Roll Key:** Press the "Roll key" to open the OSD menu; scroll the "Roll key" up and down in the menu to control the cursor; press it confirm; Scrolling up or down to control volume or brightness menu;
- Back/ Power button:** Short press to back to previous level; Press 3 seconds to turn the display on/off;
- Mini HDMI port:** Audio and video signal transmission.
- USB-C port (Full fuction):** Power supply, audio and video signal transmission;
- 3.5mm Headphone port:** Headphone, speaker expansion port

2

How to Use the Case

Lift bottom of monitor away from the case

POSITION 1

POSITION 2

3

Connect Monitor with Devices

Connect with Laptop

If your laptop has a USB-C port, connect one end of the USB-C to USB-C cable to the laptop and the other end to the monitor. Some laptops may not provide enough power to the monitor. Check the USB-C port on your laptop for the symbols shown in the table below. If you have one of the green checked symbols, then your USB-C port will provide data and enough power to the monitor. Note, MacBook ports are compatible even if there are no symbols next to it.

| | | | |
|--|---|-----------------------------------|---|
| | ✓ | | ✓ |
| | ✓ | | ✓ |
| | ✓ | | ✓ |
| | | All Apple monitors are compatible | |

* When the monitor won't turn on, connect the USB-A to USB-C cable with the monitor for charging.

4

If your laptop does not have a USB-C port, connect one end of the USB-A to USB-C cable to the laptop and the other end of the monitor. Then also connect the HDMI cable.

Connect Monitor with Devices

Connect with Phone

Only required if your device has low power USB-C ports.

*Not all phones support external. Just support the phone with USB-C3.1 protocol. When the brightness and volume are adjusted to above 80%, it is recommended to connect external power supply of 5V/2.4A or more.

Connect with iPhone (Requires lighting to HDMI adapter)

Connect with Game Console

* HDMI does not provide power

5

Description of Menu Items

| | |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <p>Brightness Menu</p> <p>⚠ Individual brightness settings will be disabled if an ECO mode other than STANDARD is selected, DCR is set to ON, or HDR is enabled</p> | <p>Brightness</p> <p>Contrast</p> <p>Black Level</p> <p>Sharpness</p> <p>⚠ Do not adjust the brightness above 80% unless you are connected to an external power supply of 5V/2.4A or greater</p> |
| <p>Image Menu</p> | <p>ECO: Preset display settings for various modes</p> <p>DCR: Enable/disable dynamic contrast ratio</p> <p>Aspect: Switches between 4:3 and wide aspect ratios</p> |
| <p>Color Temp Menu</p> | <p>Enables the adjustment of each individual RGB color, or select a warm or Cool preset level</p> |
| <p>OSD Menu (On Screen Display for monitor settings)</p> | <p>Language: Selects language for settings</p> <p>OSD Timer: Sets time-out for monitor settings menu (10-60 seconds)</p> <p>Transparency: Sets transparency of monitor settings menus</p> |
| <p>Reset Menu</p> | <p>Reset: Reset all values to factory settings</p> <p>Mute: Disables monitor audio</p> <p>Volume: Increase/ decrease audio level</p> |
| <p>Misc Menu</p> | <p>Signal Source: Selects source (USB-C or HDMI)</p> <p>Low Blue Light: Decreases blue light content in display</p> <p>HDR Mode: Enables HDR(High Dynamic Range) if connected to a compatible device</p> |

6

Specifications

| | |
|------------------|------------------------------------------------------|
| Product type | Type-C Portable Display |
| Visual area | 344.16*194.59mm |
| Screen Size | 15.6 inch |
| Panel type | IPS |
| Dimension | 368*225*8.8mm |
| Aspect ratio | 16:9 |
| Resolution | 1920*1080 |
| Display color | 16.7M |
| Visual angle | H: 85°/85°Min V: 85°/85°Min |
| Contrast ratio | 1000: 1 |
| Brightness | 250cd/m ² |
| Input interface | Mini HDMI, Type C full function, Type C power supply |
| Output Interface | 3.5mm headphone interface |
| Speaker | Built-in cavity speaker (1W*2) |

R. u. A. Bademl GbR
Sandusweg 5
35435 Wetztenberg
Germany

7